

## 460MCBM-NNA1

## Wireless Modbus TCP/IP Server to BACnet MS/TP Gateway

# **FEATURES**

- Fully configurable Modbus TCP/IP client
- Connects up to 32 Modbus TCP/IP servers
- Fully configurable BACnet MS/TP Manager
- BACnet MS/TP supports device, binary I/O/V, analog I/O/V, multi-state I/O/V, and character string value object types
- Effortless Browser
   Based Configuration,
   no programming
   software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

#### Connect Modbus TCP/IP Servers to BACnet MS/TP Devices

The 460MCBM moves data between a network of up to 32 Modbus TCP/IP servers and up to 32 BACnet MS/TP devices. Connect to your Modbus TCP servers over Wi-Fi using Wi-Fi IEEE 802.11 b/g/n at 2.4GHz with AES encryption 128-bit. It's a perfect tool to move data between your Modbus power meters, boilers, chillers, and other server devices and your BACnet MS/TP devices.

#### How Do I Use the 460MCBM-NNA1 in My Application?

For most applications, the mapping is very straightforward. Modbus register data is mapped to BACnet analog objects and Modbus coil data is mapped to binary objects. The only additional piece required for BACnet is adding metadata to each object. It really is that simple.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

# **Specification**

MODBUS TCP CLIENT FEATURES		
Operation Mode	Modbus TCP/IP Client	
Function Codes Supported	1,2,3,4,5,6, 15 & 16	
Swapping	Byte and Word Swapping	
Maximum Modbus TCP/IP Server Devices	32	
Number Read/Write Scan Lines per Server Device	200 Total - 100 reads & 100 writes	
Scan Line Support	Up to 125 Registers or 512 Coils	
BACNET MS/TP MANAGER FEATURES		
Operation Mode	BACnet MS/TP Manager Initiator	
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value	
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A	
Maximum Connections	32	
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes	
Scan Line Support	Up to 128 Objects	
INCLUDED WITH GATEWAY		
3' power cable with flying leads	5-year hardware warranty	
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life	
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff	
Manual		

ELECTRICAL / ENVIRONMENTA	NL	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	3.88
Certification	RoHS-Compliant, UL, CUL, CE Approvals	
ENCLOSURE / HARDWARE		
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
GATEWAY FEATURES & FUNCTIONS		are in Inches
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.	99999 99
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.	1.06
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.	
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	NOT EXACTLY WHAT YOU WERE LOOKING FOR? Real Time Automation offers a full line of gateway products. Give us a call at 1-800-249-1612. Or, check out a listing at <a href="https://www.rtautomation.com/products">www.rtautomation.com/products</a> . We also offer customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460MCBM-NNA1	Connects up to 32 Modbus TCP servers with as many as 32 BACnet MS/TP Subordinates













MADE IN THE USA

EXPERT SUPPORT

5-YEAR WARRANTY EM

**EMPLOYEE OWNED**